

# Suggested Operating Procedure

## Setting Up the S16 Digital Snake

### Steps

If using the S16 Snake, set this up first. The stages are:

- Set the S16 in position
- Add ethernet link
- Connect the inputs and outputs
- Configure the link

[Detailed instructions](#)

### Sound Check

Connect the inputs to the X32 Desk / S16 Snake, plus main and monitor speakers. [Suggested Setup](#)

### Display setup

The small LCDs on each channel can be configured to display the function associate with them, eg the inputs can be set to say things like “Vocal”, “Guitar”, etc and also display an icon associated with the item. The colour of the display can also be changed to help differentiate different items, eg make all vocal mics green, guitars blue, keyboards yellow.

The procedure to set up the display is:

Step	Description	Notes
1	Press “Setup”, and scroll to the Scribble Strip page.	
2	Select the channel / bus you want to configure, and then select the colour, icon and enter the name.	Choose your own colour scheme and stick to it, making it easier to spot when working live.
3	It is recommended that any unused channels have the display set to black, so that they are not a distraction	

### Mute Groups

There are 6 buttons in the Mute Group area, which can be set to mute selected channels, eg mute all instruments, mute all except house mic, mute effects, etc.

Step	Description	Notes
1	Select the “Mute Group” button on the display area (Area D)	


Step	Description	Notes
2	Press and hold a Mute Group button, and then select the channel to mute by pressing the relevant "Select" buttons	
3	Repeat for other Mute Group buttons	
4	Deselect the "Mute Group" button on the display area (Area D)	

### Suggested configuration

Mute group	Channels muted	Description
1	Mute all instruments, NOT microphones	Useful between songs for tuning / instrument changes, etc
2		
3	Mute all except house music	
4		
5	Mute All	Used to mute ALL inputs
6	Mute effects	Used to turn off effect between songs

### Gain settings

The first stage is to set up the gain and settings for each input channel.

Step	Notes
1	<p>Press the View button in the Config/Pre-amp area to bring up the relevant screen (b)</p> 
2	Select the input channel you want to set up. Make sure you are on the right Channel set, ie 1-16 or 17-32, by pressing the relevant button next to the sliders
3	Move the channel slider to Unity / zero
4	Adjust the Gain using the Gain Knob to get the required input level (a) - do this either by ear or using the input meter on the display
5	Repeat for all other inputs

# EQ Settings

The EQ panel is located at the top left of the X32 desk, as shown below:



You can access the screen menu by pressing the View button in the Equaliser area.

The easiest way so assign an EQ to each channel is to select a preset setup embedded in the desk:

- Select the channel you want to assign the EQ to
- On the menu area, select the Library button. Along the left hand side of the screen, select the elements to be loaded (Usually just Equaliser)
- Scroll down the list of options to find the nearest instrument / voice and load
- Adjust to suit the actual input, eg if you have loaded the Female vocal, adjust the low level cut to a lower frequency.

## Notes

Vocal - Male	Low cut off frequency	100Hz
Vocal - Female	Low cut off frequency	75Hz

It is useful to cut a little around the 220Hz frequency

## Adding Effects

To add an effect to a channel:

Select the channel to apply the effect to	
---	--

On the Bus Sends area, select the 13-16 bank by pressing the lowest button  
Note: 9-12 is shown selected in the image



Adjust the Bus Sends 13 & 14 which are predefined with effects (14 has Reverb) - these are the 2 lower knobs

Note: add a Mute button to Bus Sends Ch 13 & Ch 14 to switch off effect, by:

- Select "Bus Master"
- Select "Mute Group"
- Press and hold a Mute button, say "5" and then select Ch 13 & Ch 14
- Unselect the "Mute Group" button

## Performance

Assuming a single act...

### Things that may turn up

Adjusting monitor mix
Adjusting the performance mix

From:

<https://www.x32-desk.toft.org.uk/> - **Behringer X32 Manual**

Permanent link:

<https://www.x32-desk.toft.org.uk/doku.php?id=operating&rev=1739913889>

Last update: **2025/02/18 21:24**

